



## Genexis Aura E750

### Wi-Fi 7-Series

Wi-Fi 7 Residential Gateway with 2.5GE

In the continuous quest for great user experiences, your customers' home deserves the best.

The Aura E750 combines state-of-the-art hardware with best-in-class IOWRT software. Aura E750 delivers on the promise of unlocking the connected home, enabling great user experiences driven by application integrations.

The powerful memory configuration enables application download opportunities.

Wi-Fi 7 paired with 2.5GE interfaces ensures uninterrupted performance for all connected devices.

A router should match your lifestyle, be sustainable, and effortless to use. The Aura series of products meets all these needs!

#### Key features

- 802.11be (Wi-Fi 7)
- Wi-Fi EasyMesh™
- BE7200: 1.400 Mbps (2.4 GHz) + 5.800 Mbps (5 GHz)
- Multi-Link Operation (MLO)
- 4096-QAM
- Multi-RU puncturing
- High network speeds with 2.5GE WAN and 2.5GE LAN ports
- Easy setup/installation
- EasyTouch pairing with EasyMesh extenders
- Analog telephony support
- Desktop model
- Genexis CloudSight compatible

#### Sustainability features

- Housing made of 90% recycled plastics
- Designed for easy refurbishment
- Power consumption compliant to EU-CoC-BBE

#### The base for full home Wi-Fi experience with Wi-Fi EasyMesh™

The Aura is the perfect residential gateway gateway to build and steer a full home EasyMesh™ network, orchestrating multiple extenders.

Thanks to the Aura's award-winning software, subscribers are able to enjoy the outstanding Wi-Fi connectivity throughout their whole home. The Aura's steering capabilities optimize the load balance of the home network. This secures for example that running data streams, like a videocalls, that move throughout the house is allocated to the optimal access point at all times.



# Product features and specifications

## Genexis Aura E750

### General specifications

Dimensions (H x W x D)	217x170x55 mm
Weight	618 g
Power supply voltage	2.5 A
Operating temperature	0 - 40 °C
Storage temperature	-25 - 55 °C
Relative humidity	10% - 95%

### Power consumption (EU-CoC-BBE)

Aura E750	8.2 W Idle mode
-----------	-----------------

### WAN interface

1x 10/100/1000/2500 Base-T Ethernet RJ45
--

### LAN interface

2x 10/100/1000/2500 Base-T Ethernet RJ45
2x 10/100/1000 Base-T Ethernet RJ45

### WLAN interface

4x4 MU-MIMO 802.11be 2.4 GHz Wi-Fi
4x4 MU-MIMO 802.11be 5 GHz Wi-Fi

### Voice interface

1x FXS RJ11 port
------------------

### USB interface

1x USB 2.0 port
-----------------

### User interfaces

Power connector
Power switch
Reset button
Mode button
RGB status LED
End-user web-based GUI

### Wireless features

Wi-Fi MultiMedia (WMM)
Multi-Link Operation (MLO))
Wi-Fi Protected Setup (WPS)
Wi-Fi Security (WPA2 and WPA3)
Wi-Fi EasyMesh™ R4
DFS and Radar Detection
Multiple SSID and hidden SSID
Guest network SSID

### Ethernet features

IPv4 and IPv6 dual IP stack
VLAN (un)tagging, Q-in-Q, QoS
PPPoE, L2TP, IGMPv3

### Gateway features

NAT/PAT, DHCP, DNS
NTP, RTSP
Stateful Packet Inspection Firewall (SPIF)
DMZ, uPnP, Port forwarding

### Voice features

SIP based Voice-over-IP
G.711 / G.722 / G.723 codec
G.726 / G.729 codec
DTMF: In-band, RFC2833, SIP-info
3 REN support
Class 5 features
DECT CAT-iq 2.1 (optional)

### USB features

NTFS and FAT32 file system storage devices
--

### Management and control

TR-069, TR369
TR-181, TR-104 data models
Command Line Interface (CLI)
Web based GUI
Genexis EasyWiFi App
Genexis CloudSight
Fail-safe firmware upgrade

### Regulatory compliance

Radio Equipment Directive 2014/53/EU
EU-CoC-BBE power consumption
Energy Related Products Directive 2009/125/EC
CE Safety Directive 2014/35/EU
UKCA Safety Regulations 2016
RoHS and REACH Directive 2011/65/EU
ITU-T K.21 standard compliancy

### Package content

Aura E750
Power supply unit
Ethernet cable
Quick installation guide

## Genexis Aura Series product models

Model	Uplink WAN (Mbps)	LAN (Mbps)		Wi-Fi 4x4 2.4 GHz	Wi-Fi 4x4 5.0 GHz	FXS	USB	DECT
Aura E750	100/1000/2500	2x 2x	100/1000/2500 100/1000	11be	11be	1x	1x	n/a
Aura E755	100/1000/2500	2x 2x	100/1000/2500 100/1000	11be	11be	1x	1x	1x

Note: No rights can be derived from this publication. Not every listed feature may be included in the shipping product. We reserve the right to make changes without prior notice.